





## Single Phase (1 MOV Modules and 1 GDT module) Surge Protection Device JDA D1-50/150-VG-R

Surge arrester for low-voltage power supply system protection against surges at the boundaries from lightning protection zone 0B-1 and higher.

- Class I+II (B+C) arrester in accordance with IEC61643-11:2011, UL1449 3rd.
- Two part design consisting of base and plug-in protection module.
- High energy MOV (Metal Oxide Varistor) and Gas Discharge Tube (GDT) inside.
- Reliable supervision due to disconnection device.
- Fault indication by red indication flag in window.
- Fast response.
- With remote alarm terminal optional.



### Technical Data

Type	D1-50/150-VG-R	
Nominal Voltage	110Vac	
In accordance with	IEC61643-11:2011; UL1449 3rd	
Category IEC/VDE	I+II/B+C	
Max. continuous operating voltage (AC/DC)	L-N	150/200
	N-PE	255
Nominal discharge current (8/20) In	L-N	7kA
	N - PE	25kA
Max. discharge current(8/20) I <sub>max</sub>	L-N	50kA
	N - PE	50kA
Lightning impulse current(10/350) I <sub>imp</sub>	L-N	7kA
	N - PE	25kA
Voltage protection level	L-N@I <sub>n</sub>	<0.8kV
	N-PE(1.2/50)	<1.5kV
Response time	L-N	≤25 ns
	N-PE	≤100 ns
Follow current	L-N	No
	N-PE	100Arms@U <sub>c</sub>
Backup fuse(only required if not already provided in mains)	160A gL/gG	
Operating temperature range	- 40°C ~ + 80°C	
Cross-section of connection wire	Single-strand 35mm <sup>2</sup> ; multi-strand 25mm <sup>2</sup>	
Mounting	35mm DIN-rail in accordance with EN 50022/DIN46277-3	
Enclosure material	thermoplastic; extinguishing degree UL94 V-0	
Degree of protection	IP20	
Installation width	2 modules, DIN 43880	
Thermal disconnecter	Internal green – normal red - failure	
Remote alarm contact	Yes	

note: subject to change without any notice, JDA pay no responsibility