

## **PV 40/100-MVCR**

Common mode DC Surge arrester for DC system protection against surges at the boundaries from lightning protection zone 0B-1 and higher.

- Class II (C) DC arrester in according with IEC61643-1:2005.
- Two part design consisting of base and plug-in protection module.
- · Common protection mode.
- High energy MOV (Metal Oxide Varistor) inside.
- Reliable supervision due to disconnection device.
- · Fault indication by red indication flag in window.
- · Fast response.
- · With remote alarm terminal.





## **Characteristics**

Туре	PV40/100-MVCR
In accordance with	IEC61643-1:2005 ; UL1449 ed.3
Category IEC/VDE	II/C
Protection Mode	Common mode
Max. continuous operating voltage (DC)	100VDC
Nominal discharge current (8/20) In	20KA
Max. discharge current(8/20) Imax	40KA
Voltage protection level	800V
Response time	≤25 ns
Backup fuse (only required if not already provided in mains)	125A gL/gG
Operating temperature range	- 40°C + 80°C
Cross-section of connection wire	Single-strand 35 <sub>mm</sub> <sup>2</sup> ; multi-strand 25 <sub>mm</sub> <sup>2</sup>
Mounting	35 <sub>mm</sub> DIN-rail in accordance with EN 50022/DIN46277-3
Enclosure material	Thermoplastic; extinguishing degree UL94 V-0
Degree of protection	IP20
Installation width	2 module , DIN 43880
Thermal disconnector	Internal green – normal red - failure
Remote alarm contact	Yes
Additional data for Remote Alarm Contacts	
Remote alarm contact type	floating changeover contact
Switching capability UN/IN	AC: 250V/0.5A DC: 250V/0.1A; 125V/0.2A; 75V/0.5A
Cross-section of connection wire	Max. 1.5 <sub>mm</sub> <sup>2</sup>

## Note: Subject to change without any notice.

## **Dimensions and Diagram**





note: subject to change without any notice, JDA pay no responsibility